



## Compatible Dimmers

Dimmer Details			Dimming Characteristics			
Brand	Model	Dimming Mode	Dimming Type	Dimming Range	Max No. Lamps	Pass / Fail
Zano	ZMO150	Trailing Edge	Rotary	0 > 100%	10	Pass
Varilight	MJP120 (V PRO)	Trailing Edge	Rotary	22 > 100%	10	Pass
Varilight	JQP401W	Trailing Edge	Rotary	22 > 100%	10	Pass
Varilight	JCE101	Trailing Edge	Touch	15 > 100%	10	Pass
Varilight	IJFSI101	Trailing Edge	Touch	37 > 100%	10	Pass
Knightsbridge	VFR200M	Trailing Edge	Rotary	22 > 100%	10	Pass
Click	MD9014	Trailing Edge	Rotary	10 > 100%	10	Pass
Aurora	AU-A1ZB2WDM	Trailing Edge	Rotary	16 > 100%	10	Pass
Schneider	GU6012L	Trailing Edge	Rotary	16 > 100%	10	Pass
Deta	8629WH	Trailing Edge	Rotary	Not Verified	10	Pass
BG	FBS81P	Trailing Edge	Rotary	Not Verified	10	Pass
Lightwave RF	L21EU	Trailing Edge	2 Push Button	29 > 100%	10	Pass

Want to use a different dimmer? We can test it.

If you have any questions or would like a demonstration please get in touch.

hello@lumi-plugin.com +44 (0)33 0380 1329

